

Manual Pull Station

Model No	: S-341
Application	: Indoor
Adopted voltage	: DC ~ 18 ~ 28V (DC-24)
Adopted current	: 100 mA
Function	: Push Button Emergency, Phone Jack, Reset Switch, confirmation LED lamp
Color	: Red
Size	: 140 mm. x 40 mm.
Weight	: 270 g
Joint volume	: DC - 30V 1A



S-341

Manual Base



Model	: S-342
Material	: ABS
Color	: Red
Size	: 140 mm. x 50 mm.

S-342

Alarm Siren / Strobe

Model	: S-350
Input Voltage Range	: 24V DC (12~30V DC)
Operation Current	: Fire Bell with Strobe
(at 24V DC)	LED : 50 mA (Max : 65 mA)
Strobe	: Over 8,000m cd. (6pcs Super bright LED)
Sound Output	: 100± 5dB at 1 m.(24V DC)
Tone Type	: Alarm Siren
Operation Temperature	: -10 °C~+ 60 °C
Continue Operation Test:	Over 72 Hours
(at 24 V DC)	
Life Test	: "ON" 1 minute, "OFF" 30 seconds, Duty Cycle (at 24 V DC) Continuously over 500 Hours period



S-350

Alarm Strobe



S-349

Model	: S-349
Input Voltage Range	: 24V DC (12 30V DC)
Alarm Current	: 22mA @ 24V
Sound Output	: 100+5dB@24V
Tone Type	: Sweep Siren
Operation Temp	: -10 °C ~ +60 °C